

# Go Direct<sup>®</sup> Wide-Range Temperature (Order Code GDX-WRT)



This rugged temperature probe features a wide temperature range, from  $-20^{\circ}\text{C}$  to  $330^{\circ}\text{C}$ . The high upper limit of the sensor allows for melting point determinations of most organic compounds. It uses platinum RTD (Resistance Temperature Detector) technology to establish a  $\pm 0.5^{\circ}\text{C}$  accuracy or better, as well as excellent stability and repeatability. Each unit is individually calibrated, and the calibration is stored on the sensor. It is designed to be used as you would use a thermometer for experiments in organic and inorganic chemistry, physics, biology, Earth science, and environmental science.

**Note:** Vernier products are designed for educational use. Our products are not designed nor are they recommended for any industrial, medical, or commercial process such as life support, patient diagnosis, control of a manufacturing process, or industrial testing of any kind.

## What's Included

- Go Direct Wide-Range Temperature
- Micro USB Cable

## Compatible Software

See [www.vernier.com/manuals/gdx-wrt](http://www.vernier.com/manuals/gdx-wrt) for a list of software compatible with Go Direct Wide-Range Temperature.

## Quick Start: Vernier Graphical Analysis<sup>®</sup> and Bluetooth<sup>®</sup>

1. Charge your sensor for at least 2 hours before first use.
2. Turn on your sensor. The LED will blink red.
3. Launch Graphical Analysis, then click **Sensor Data Collection**.
4. Select your sensor from the list. The sensor ID is located on the sensor label near the bar code. **Note:** If you don't see a list of available sensors, click **WIRELESS**. After selecting your sensor, click **Pair**.
5. This is a multi-channel sensor. Click **SENSOR CHANNELS** and select the channel(s) you want to use.
6. Click **DONE**. You are now ready to collect data.

## Using other Vernier data-collection apps or want to connect via USB?

Visit [www.vernier.com/start-go-direct](http://www.vernier.com/start-go-direct)

**Note:** This sensor also works with LabQuest 2 and LabQuest 3; it does not work with the original LabQuest.

## Charging the Sensor

Connect Go Direct Wide-Range Temperature to the included Micro USB Cable and any USB device for two hours.

You can also charge up to eight Go Direct Wide-Range Temperature Probes using our Go Direct Charge Station, sold separately (order code: GDX-CRG). An LED on each Go Direct Wide-Range Temperature indicates charging status.

|               |   |
|---------------|---|
| Charging      | Blue LED on steady while sensor is connected to the Charging Cable or Charging Station. |
| Fully charged | Blue LED is off when charging is complete.  |

## Providing Power

|                                  |   |
|----------------------------------|---|
| Turning on the sensor            | Press button once. Red LED indicator flashes when unit is on.   |
| Putting the sensor in sleep mode | Press and hold button for more than three seconds to put into sleep mode. Red LED indicator stops flashing when sleeping. |

## Connecting the Sensor

See the following link for up-to-date connection information:

[www.vernier.com/start/gdx-wrt](http://www.vernier.com/start/gdx-wrt)

## Connecting via Bluetooth

|                  |  |
|------------------|--|
| Ready to connect | Red LED flashes when sensor is awake and ready to connect via Bluetooth. |
| Connected        | Green LED flashes when sensor is connected via Bluetooth.                |

## Connecting via USB

|   |  |
|---|--|
| Connected and charging                    | Blue and Green LED solid when sensor is connected to Graphical Analysis via USB and unit is charging. (Green LED is obscured by the blue one.) |
| Connected, fully charged                  | Green LED solid when sensor is connected to Graphical Analysis via USB and the unit is fully charged.  |
| Charging via USB, connected via Bluetooth | Blue LED is solid and green LED is flashing, but the green flashing LED looks white because it is overwhelmed by the blue.                     |

## Identifying the Sensor

When two or more sensors are connected, the sensors can be identified by tapping or clicking Identify in Sensor Information.

## Using the Product

Connect the sensor following the steps in the Quick Start section of this user manual.

**Important:** When using this sensor, keep in mind that important electronic circuitry is built into the handle of the probe. For optimal accuracy of the RTD, keep the handle of the probe from warming above 40°C (104°F). If necessary, shield the handle from high-temperature sources using aluminum foil or other shielding material.

## Calibration

Go Direct Wide-Range Temperature will never need to be calibrated. Each probe is carefully calibrated before it ships, and this unique calibration is stored on the sensor.

## Specifications

|   |  |
|---|--|
| Temperature range   | -20°C to 330°C   |
| Maximum temperature that the sensor can tolerate without damage | 380°C  |
| Temperature sensing element                                     | Platinum RTD (100 Ω)   |
| Accuracy  | ±0.3°C at 0°C<br>±0.2°C at 100°C<br>±0.5°C at 300°C  |
| Response time from 25°C to 100°C in water                       | 30 seconds   |
| Probe dimensions  | Probe length (handle plus body): 28 cm<br>Stainless steel body:<br>length 17 cm,<br>diameter 6.4 mm<br>Probe handle:<br>length 11 cm,<br>width 3 cm.5,<br>thickness 1.7 cm |

## Care and Maintenance

**Probe Chemical Tolerance:** The stainless-steel probe body is constructed from grade 316 stainless steel. This high-grade stainless steel provides a high level of corrosion resistance for use in the science laboratory. Here are some general guidelines for usage:

- The probe handle is constructed of molded plasticized Santoprene®. While this material is very chemical resistant, we recommend that you avoid submerging the probe beyond the stainless steel portion.
- Always wash the probe thoroughly after use.
- The probe can be left continuously in water at temperatures within the range of -20°C to 330°C. Continuous usage in saltwater will cause only minor discoloration of the probe, with no negative effect on performance.
- You can leave the probe continuously in most organic compounds, such as methanol, ethanol, 1-propanol, 2 propanol, 1-butanol, n-hexane, lauric acid, paradichlorobenzene, phenyl salicylate, and benzoic acid. The probe should not be left in n-pentane for more than one hour.
- The probe can be left in strong basic solutions, such as NaOH, for up to 48 hours, with only minor discoloration. We do not recommend usage in basic solutions that are greater than 3 M in concentration.
- The chart provides the maximum length of time we recommend for probe exposure to some common acids. Probes left in an acid longer than these times may bubble and/or discolor, but will still be functional. We do not recommend probes be left to soak in any acid longer than 48 hours.

| Maximum acid exposure time         |          |
|------------------------------------|----------|
| 1 M HCl                            | 20 min   |
| 2 M HCl                            | 10 min   |
| 3 M HCl                            | 5 min    |
| 1 M H <sub>2</sub> SO <sub>4</sub> | 48 hours |
| 2 M H <sub>2</sub> SO <sub>4</sub> | 20 min   |
| 3 M H <sub>2</sub> SO <sub>4</sub> | 10 min   |

## Battery Information

Go Direct Wide-Range Temperature contains a small lithium-ion battery in the handle. The system is designed to consume very little power and not put heavy demands on the battery. Although the battery is warranted for one year, the expected battery life should be several years. Replacement batteries are available from Vernier (order code: GDX-BAT-300).

## Storage and Maintenance

To store Go Direct Wide-Range Temperature for extended periods of time, put the device in sleep mode by holding the button down for at least three seconds. The red LED will stop flashing to show that the unit is in sleep mode. Over several months, the battery will discharge but will not be damaged. After such storage, charge the device for a few hours, and the unit will be ready to go.

Exposing the battery to temperatures over 35°C (95°F) will reduce its lifespan. If possible, store the device in an area that is not exposed to temperature extremes.

## Water Resistance

The body of the Go Direct Wide-Range Temperature Probe is not water resistant and should never be immersed in water.

If water gets into the device, immediately power the unit down (press and hold the power button for more than three seconds). Disconnect the sensor and charging cable, and remove the battery. Allow the device to dry thoroughly before attempting to use the device again. Do not attempt to dry using an external heat source.

## How the Sensor Works

The detector is a platinum RTD (Resistance Temperature Detector) sensor with an output that increases nonlinearly with increasing temperature.

## Troubleshooting

For troubleshooting and FAQs, see [www.vernier.com/til/4038](http://www.vernier.com/til/4038)

## Repair Information

If you have watched followed the troubleshooting steps and are still having trouble with your Go Direct Wide-Range Temperature, contact Vernier Technical Support at [support@vernier.com](mailto:support@vernier.com) or call 888-837-6437. Support specialists will work with you to determine if the unit needs to be sent in for repair. At that time, a Return Merchandise Authorization (RMA) number will be issued and instructions will be communicated on how to return the unit for repair.

## Accessories/Replacements

| Item                                  | Order Code     |
|---------------------------------------|----------------|
| Micro USB Cable                       | CB-USB-MICRO   |
| USB-C to Micro USB cable              | CB-USB-C-MICRO |
| Go Direct 300 mAh Replacement Battery | GDX-BAT-300    |

## Warranty

Warranty information for this product can be found on the Support tab at [www.vernier.com/gdx-wrt](http://www.vernier.com/gdx-wrt)

General warranty information can be found at [www.vernier.com/warranty](http://www.vernier.com/warranty)

## Disposal

When disposing of this electronic product, do not treat it as household waste. Its disposal is subject to regulations that vary by country and region. This item should be given to an applicable collection point for the recycling of electrical and electronic equipment. By ensuring that this product is disposed of correctly, you help prevent potential negative consequences on human health or on the environment. The recycling of materials will help to conserve natural resources. For more detailed information about recycling this product, contact your local city office or your disposal service.

Battery recycling information is available at [www.call2recycle.org](http://www.call2recycle.org)

Do not puncture or expose the battery to excessive heat or flame.



The symbol, shown here, indicates that this product must not be disposed of in a standard waste container.

## Federal Communication Commission Interference Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

### FCC Caution

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference and
- (2) this device must accept any interference received, including interference that may cause undesired operation

### RF Exposure Warning

The equipment complies with RF exposure limits set forth for an uncontrolled environment. The antenna(s) used for this transmitter must not be co-located or operating in conjunction with any other antenna or transmitter. You are cautioned that changes or modifications not expressly approved by the party responsible for compliance could void your authority to operate the equipment.

## IC Statement

This device complies with Industry Canada license-exempt RSS standard(s). Operation is subject to the following two conditions:

- (1) this device may not cause interference, and
- (2) this device must accept any interference, including interference that may cause undesired operation of the device.

**Industry Canada - Class B** This digital apparatus does not exceed the Class B limits for radio noise emissions from digital apparatus as set out in the interference-causing equipment standard entitled "Digital Apparatus," ICES-003 of Industry Canada. Operation is subject to the following two conditions: (1) this device may not cause interference, and

- (2) this device must accept any interference, including interference that may cause undesired operation of the device.

To reduce potential radio interference to other users, the antenna type and its gain should be so chosen that the equivalent isotropically radiated power (e.i.r.p.) is not more than that permitted for successful communication.

**RF exposure warning:** The equipment complies with RF exposure limits set forth for an uncontrolled environment. The antenna(s) used for this transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes :

- (1) l'appareil ne doit pas produire de brouillage, et
- (2) l'appareil doit accepter toute interférence radioélectrique, même si cela résulte à un brouillage susceptible d'en compromettre le fonctionnement.

Cet appareil numérique respecte les limites de bruits radioélectriques applicables aux appareils numériques de Classe B prescrites dans la norme sur le matériel interférant-brouilleur: "Appareils Numériques," NMB-003 édictée par industrie Canada. L'utilisation est soumise aux deux conditions suivantes:

(1) cet appareil ne peut causer d'interférences, et

(2) cet appareil doit accepter toutes interférences, y comprises celles susceptibles de provoquer un dysfonctionnement du dispositif.

Afin de réduire les interférences radio potentielles pour les autres utilisateurs, le type d'antenne et son gain doivent être choisis de telle façon que l'équivalent de puissance isotrope émise (e.i.r.p) n'est pas plus grand que celui permis pour une communication établie.

**Avertissement d'exposition RF:** L'équipement est conforme aux limites d'exposition aux RF établies pour un environnement non supervisé. L'antenne (s) utilisée pour ce transmetteur ne doit pas être jumelée ou fonctionner en conjonction avec toute autre antenne ou transmetteur.

**Note:** This product is a sensitive measurement device. For best results, use the cables that were provided. Keep the device away from electromagnetic noise sources, such as microwaves, monitors, electric motors, and appliances.



Vernier Science Education  
13979 SW Millikan Way • Beaverton, OR 97005-2886  
Toll Free (888) 837-6437 • (503) 277-2299 • Fax (503) 277-2440  
info@vernier.com • www.vernier.com

Rev. 7/3/2024

Go Direct, Vernier Graphical Analysis, LabQuest, and other marks shown are our trademarks or registered trademarks in the United States. All other marks not owned by us that appear herein are the property of their respective owners, who may or may not be affiliated with, connected to, or sponsored by us.

The Bluetooth® word mark and logos are registered trademarks owned by the Bluetooth SIG, Inc. and any use of such marks by Vernier Science Education is under license. Other trademarks and trade names are those of their respective owners.

