

Stir Station

(Order Code STIR)

The Stir Station is a multi-function magnetic stirrer. It includes the following features

- Works efficiently with beakers from 50 mL to 1 L in size and a wide range of sizes and shapes of magnetic stirring bars; stirring capacity of 800 mL in a 1 L beaker
- Stirring speed range of 50–1250 RPM
- Stirring platform is lit with 3 white, cool LEDs
- Ring stand post is conveniently positioned and affixed to the stirrer base, 4 inches from the center of the stirring platform; ideal for use with the Vernier Drop Counter
- Runs on 6-volt DC power adapter (included) or 4 C batteries (not included)



Note: Vernier products are designed for educational use. Our products are not designed nor are they recommended for any industrial, medical, or commercial process such as life support, patient diagnosis, control of a manufacturing process, or industrial testing of any kind.

What's Included

- Stir Station unit
- stirring bar (4 cm)
- Vernier Microstirrer
- ring stand post (46 cm)
- 6-volt DC power adapter

Getting Started

1. Connect the 6-volt DC power adapter (included) to the Stir Station and to an outlet.
2. To use the Stir Station with batteries, remove the battery compartment cover from the underside of the unit, insert four C batteries, and replace the compartment cover.
3. Install the ring stand post.
4. Place a magnetic stirring bar in the beaker of water and turn on the Stir Station.

For full product documentation, see

www.vernier.com/start/stir

Using the Product

The Stir Station's ring-stand post makes it a perfect complement to the Vernier Drop Counter (shown here) as your students conduct titration experiments. Simply connect the Drop Counter to the ring stand post and position a buret clamp and reagent reservoir to deliver the titrant dropwise to a container of liquid. Using DataDrop program on a TI graphing calculator or Data Pro (1.15 or newer) on a Palm OS® handheld you can collect data and view plots of pH vs. volume, first derivative vs. volume, or second derivative vs. volume.



Specifications

| | |
|--------------------------------------|--|
| Stirring quantity maximum | 800 mL |
| Speed range | 50–1250 RPM |
| Speed Control: stepless | stepless |
| Stirring platform material | ABS plastic |
| Diameter of stirring platform | 10 cm |
| Weight, without batteries | 460 g |
| Permissible ambient temperature (°C) | 0–60 °C |
| Permissible relative moisture (%) | 90% |
| Power supply | 6-volt AC adapter (included) or four C dry cell batteries |
| Installation category | II |

Care and Maintenance

- Although the ring stand post is firmly seated in a metal-reinforced, threaded collar, do not lift the Stir Station by the ring stand post to move it.
- The Stir Station is a mechanical device with many moving parts. It is best to turn off the Stir Station motor and the LED lights when the device is not in use.
- Under normal operating conditions, the Stir Station will run in excess of 100 hours on battery power, without the lights. When you use the Stir Station with batteries, as the batteries run down you may notice the lights dimming. The stirring motor will continue to run but the maximum stirring speed may be compromised.
- The stirring platform of the Stir Station is made of ABS plastic. ABS, or acrylonitrile butadiene styrene, was selected because of its strength, rigidity, and toughness. It has good chemical and stress-cracking resistance. Even so, it is wise to clean spills promptly, following the normal guidelines used in dealing with chemical spills. Many stains can be removed from the stirring platform with soap and water. Never immerse the unit or flood it with water or other liquids.
- When using the Vernier Microstirrer, it is best to position the Microstirrer slightly off center of the beaker. Rotate the Microstirrer to find the smoothest and quietest operating position.
- The stirring controls are sufficiently steady on the Stir Station that you can set the stirring at a desired speed and it will not change appreciably over several hours.

How the Sensor Works

The Stir Station uses a tachometer feedback control system, thus making it easier to fine-tune and maintain its stirring speed. This method of speed control also allows you to remove a beaker while it is stirring without affecting the Stir Station's motor speed.

Three LEDs are positioned beneath the translucent stirring platform and offer efficient lighting for a wide range of beaker sizes. The LEDs do not heat the stirring platform and have a long life span so they will most likely never need replacing.

The Stir Station motor is sufficiently powerful to operate most common-size magnetic stirring bars. It will stir solutions of a viscosity nearing the 1000-centipoise range (roughly half the viscosity of grocery store corn syrup). You may also use a Vernier Microstirrer (included) with the Stir Station.

Troubleshooting

For troubleshooting and FAQs, see www.vernier.com/tit/1387

Repair Information

If you have watched the related product video(s), followed the troubleshooting steps, and are still having trouble with your Stir Station, contact Vernier Technical

Support at support@vernier.com or call 888-837-6437. Support specialists will work with you to determine if the unit needs to be sent in for repair. At that time, a Return Merchandise Authorization (RMA) number will be issued and instructions will be communicated on how to return the unit for repair.

Accessories/Replacements

| Item | Order Code |
|--------------------|------------|
| Microstirrer | MSTIR |
| Vernier AC Adaptor | IPS |

Warranty

Warranty information for this product can be found on the Support tab at www.vernier.com/stir

General warranty information can be found at www.vernier.com/warranty

Safety

The Stir Station contains strong magnets. It should not be used near Cardiac pacemakers, CDs, cassette tapes, or other similar data storage devices. The Stir Station is not designed to be used under water.

Disposal

When disposing of this electronic product, do not treat it as household waste. Its disposal is subject to regulations that vary by country and region. This item should be given to an applicable collection point for the recycling of electrical and electronic equipment. By ensuring that this product is disposed of correctly, you help prevent potential negative consequences on human health or on the environment. The recycling of materials will help to conserve natural resources. For more detailed information about recycling this product, contact your local city office or your disposal service.



Vernier Science Education
13979 SW Millikan Way • Beaverton, OR 97005-2886
Toll Free (888) 837-6437 • (503) 277-2299 • Fax (503) 277-2440
info@vernier.com • www.vernier.com

Rev. 10/28/2024

Data Pro and other marks shown are our trademarks or registered trademarks in the United States.

TI-Nspire is a trademark of Texas Instruments.

All other marks not owned by us that appear herein are the property of their respective owners, who may or may not be affiliated with, connected to, or sponsored by us.